

LINEAR AMPLIFIER  
AMPLIFICATORE LINEARE

# KL 203



<b>Frequency / Frequenza:</b>	<b>28-29.7 MHz</b>
<b>Power Supply / Alimentazione:</b>	<b>12-14Vcc</b>
<b>Input Current / Assorbimento:</b>	<b>10A max</b>
<b>Input Power / Potenza d'Ingresso:</b>	<b>0.5-10W</b>
<b>Output Power / Potenza d'Uscita:</b>	<b>100W</b>
<b>Input VSWR / ROS di Ingresso:</b>	<b>1.1-1.5:1</b>
<b>Mode / Funzionamento:</b>	<b>AM/FM/SSB</b>
<b>Fuse / Fusibile:</b>	<b>12A</b>

VOX RTX Switching. Protection against inverse polarity. 24 months warranty, (not including RF transistors / aesthetic damage). The use on 27MHz band is forbidden and that the use of linear amplifiers is ruled by specific laws that are to be understood by the user. The manufacturer declines any responsibility from unlawful use. If this device is installed in a vehicle the vehicle must be stationary before use.

**ATTENTION:** This product complies with CE standards if used in conjunction with RM 27/586 external Low Pass Filter connected between the KL203 (ANT) Output and Antenna.

Commutazione Elettronica. Protezione contro l'inversione di polarità. Garanzia 24 mesi, (Le parte estetiche ed i transistor finali non sono inclusi). L'utilizzo sui 27MHz è proibito, ricorda che l'utilizzo degli amplificatori lineari è regolato da specifiche leggi, che devono essere conosciute dall'utilizzatore, in ogni caso il produttore declina ogni responsabilità derivante da un utilizzo non corretto. L'uso di questo apparato è ammesso solo con veicolo fermo.

**ATTENZIONE:** L'apparato è conforme alle norme CE se usato in combinazione con il filtro 27/586 collegato tra l'uscita a radiofrequenza dell'apparato (ANT) e l'antenna.